

GLX-PCB-RITE

NEW MENU SETTING REQUIRED!

Because this replacement mainboard is used to replace various models, it must be configured to operate your pool's Turbo Cell before operation. After installing the board, refer to the steps below to correctly configure the board for use with the installed Turbo Cell. Failure to perform this step may result in inaccurate salt readings, improper operation, and possible system shut-down.

Determine the model of the installed Turbo Cell which can be found on its colored label. Refer to the following information and steps below to set the Turbo Cell type.

"t-3" = T-CELL-3, GLX-CELL-3-W
"t-5" = GLX-CELL-5, GLX-CELL-5-W
"t-9" = T-CELL-9, GLX-CELL-9-W
"t-15" = T-CELL-15, GLX-CELL-15-W

1. Slide the Main Switch to the "Auto" position.
2. Push the Diagnostic button repeatedly until "t-xx" appears on the display ("t-15" is the factory default). If the desired cell type is displayed skip to step 4.
3. To change to a different cell type, slide the Main Switch from "Auto" to "Super Chlorinate" and back to "Auto". Repeat this process until the desired cell type is displayed.
4. Push the Diagnostic button to exit.

The GLX-PCB-RITE has now been configured and is ready to start normal operation.

T-CELL-3 GLX-CELL-3-W

NEW MENU SETTING REQUIRED!

You must configure your controller for use with the T-CELL-3 or GLX-CELL-3-W chlorinator cell *before* attempting to operate. Incorrect configuration will cause inaccurate salt readings, improper operation, and possible system shutdown.

The T-CELL-3 and GLX-CELL-3-W are designed for pools up to 15,000 gallons. They are compatible with the following models only and will NOT work with earlier versions:

- AQR (Aqua Rite - all 2009 or later) - firmware version 1.5 or later
- AQR-PRO (Aqua Rite Pro) - operating with firmware 1.10 or later
- PL-P-4 (Pro Logic P4) - operating with firmware 4.10 or later
- PL-PS-x (Pro Logic PS) - operating with firmware 4.10 or later

T-cell 3

Connecting to an AQR:

1. Slide the Main Switch to the "Auto" position.
2. Push the Diagnostic button repeatedly until "t-xx" appears on the display ("t-15" is the factory default).
3. To change cell type, slide the Main Switch from "Auto" to "Super Chlorinate" and back to "Auto". Repeat this process until the "t-3" is displayed.
4. Push the Diagnostic button to exit.

Connecting to an AQR-PRO:

1. Verify that the firmware version is 1.10 or greater by pushing the "Info" button, then ">" repeatedly until the firmware revision is shown. If the firmware version is less than 1.10, the T-CELL-3 or GLX-CELL-3-W cannot be used.
2. Access the Settings Menu by pushing the "Settings" button.
3. Push ">" until Chlor. Config is displayed, then push "+".
4. Push ">" repeatedly until "Cell Type" is displayed.
5. Push "+" or "-" until "T-CELL-3" is displayed.
6. Exit Settings Menu by pushing the "Info" button.

Connecting to a PL-P-4 or PL-PS-x:

1. Verify that the firmware version is greater than 4.10 by entering the Diagnostic Menu and repeatedly pushing the ">" until the Main Firmware revision is shown. If the firmware version is less than 4.10, the T-CELL-3 or GLX-CELL-3-W cannot be used.
2. Enter the Configuration Menu.
3. Push ">" until Chlor. Config is displayed, then push "+".
4. With the Chlorinator Enabled, push ">" repeatedly until "Cell Type" is displayed.
5. Push "+" or "-" until "T-CELL-3" is displayed.
6. Exit Settings Menu by pushing the "Menu" button.